


Hours

Minutes

Seconds



4093 pin 14 +5V pin 7 GND

Use CD4511 if 4513 is not available, but circuit has to be changed a bit around 4511

pin 16 +5V pin 8 GND

A Thumbwheel Switch has to be used in place of DIP switch shown, just know that 1-2-4-8 nibble (4 bit) should be generated by Thumbwheel switch at preset or jam inputs of 4029.

Resistor array used to simplify my work, use separate resistors if that is what you have.

use 74HCT40XX chips in place of CD40XX for only 5V and high speed designs. Use Shrink sleeves and proper gauge of wire. put 104 CD cap for all ICs from positive to negative close to IC, even if omitted in circuit, for opamps on dual supply two caps. unused inputs of logic and opamps pull up or down to avoid oscillations and noise. connect supply of all chips if not mentioned. "analog ground" and "digital ground" must be linked at power supply only, avoid loops, let grounds radiate from a ground plane. use MFR 1% for all Resistors, 33E means 33 ohms, 22K means 22 kilo ohms, 1M is 1 megohm. 10T tp means ten turn trimpot. '474 CD' is 47 with 4 zeros pF, 470000 pF, 470 nF, 0.47uF, ceramic disc. "pl" is plastic, low leakage multilayer.

delabs design
delabs-circuits.com
delabs.net

delabs circuits and technologies		
Title	Digital Timer Clock With Preset	
Size B	Document Number	del20029
File	Tuesday, December 14, 2004	Sheet 1 of 1
		Rev 2